

RENTAL LAB-TC

ADVANCED HIGH POWER DC SOURCES



The LAB-TC range is a highly advanced series of programmable DC power supplies. The unit can be provided in a flight case with a full electrical integration.

Constant voltage, current and power operating modes are provided. The internal resistance can be adjusted making the LAB-TC ideal for battery simulation. Remote sense is provided to compensate for the voltage drop in the load lines. All regulation, monitoring and communication tasks are conducted by high performance micro-controllers and digital signal processors. This provides exceptional accuracy, reproducibility and long term stability. The DC source is fitted with an analogue and RS-232 interface.

- + Can be Optimised for Individual Loads
- + Adjustable Internal Resistance
- + Embedded Function Generator
- + Battery Emulation Software
- + Solar Array Simulation GUI
- + Full Digital Regulation

CONTENTS

Selection Table	2
Modularity (Master/Slave)	2
Form Factor & Enclosures	2
Operating Ranges & Features	3-4
Interfaces & Control	5
Software/Soft Tools	6
Application Specific GUIs	7
New LAB-TC Systems	8
Common LAB-TC Applications	8

SELECTION TABLE

SELECTION TABLE

SELECTION TABLE			
Part Number	Max. Power	Voltage Range	Current Range
LAB-TC 2-46-r	2kW	0 to 46V	0 to 43A
LAB-TC 32-65-r	32kW	0 to 65V	0 to 600A
LAB-GSS+TC 64-130-r*	64kW	0 to 130V	0 to 600A

* Comprised of 1 × unidirectional LAB-TC 32-65 module and 1 × bidirectional LAB-GSS 32-65 module in series connection.

MODULARITY (MASTER/SLAVE)

The 64kW system is comprised of a 65V LAB-GSS and LAB-TC in series connection. The units are not in master/slave connection and operate in source mode only. Each module is able to operate independently, so that systems can be reconfigured, expanded or broken up as needs dictate. Inbuilt system comms allow users to switch between various set-ups.

The modular approach is useful for test houses and research labs who regularly test different sized power devices. Individual modules can be used for the day to day testing of multiple small devices, then grouped together for larger projects.

Our rental systems can be combined in series, parallel or matrix configurations with any LAB-TC or LAB-GSS modules you have previously purchased, providing they have the same nominal outputs. Up to 64 modules can be connected in this way. This allows any short term requirements outside of usual operating ranges to be met.

FORM FACTOR AND ENCLOSURES

A series of cabinets are used to make deployment of our high power LAB-TC and LAB-GSS rental modules simpler, quicker and safer.

Among the available safety features is a status indicator that alerts users of any residual energy on the DC link that is greater than 15V. This operates even if the mains power is turned off. Another indicator assesses the quality and correct rotation of the AC input voltage and illuminates if correct. Panel mounted DC sockets are both mechanically keyed and colour coded to eliminate any possible user errors.

Specific features vary per cabinet, please contact ETPS to discuss an exact cabinet.

Common features include:

- + All 4 Heavy Duty Castors with Locking Function
- + Passive Indication of Connected Line Voltage
- Passive Indication of DC Output Voltage
- 5m DC Cable Sets with Ring Terminals
- + Panel Mounted Emergency Stop







OPERATING RANGES AND FEATURES

LAB-TC TECHNICAL DATA

GENERAL				
Operating Modes	Constant Voltage [0 - 100% of _{VMAX}] Constant Current (0 - 100% of I _{MAX}] Constant Power (5 - 100% of P _{MAX})			
Input Voltage	65V module: 3 × 360 - 440 VAC 46V module: 230VAC			
Line Frequency	48 - 62Hz			
Mains Connection Type	65V module: 3L + PE (no neutral) 46V module: 13A IEC C13			
Internal Resistance Range	Adjustable $\Omega_{MAX} = [V_{NOM} / I_{NOM}]$			
Interfaces	Analogue & RS-232			
Remote Sense	0 - V _{MAX} + 2%			
Efficiency	Up to 95%			
Load Regulation (CV, CC)	<± 0.1%			
Line Regulation (CV, CC)	<± 0.1%			
Response time (10-90%)	<2ms			
Over Voltage Protection	0 - 110% of V _{MAX}			
Over Current Protection	0 - 110% of I _{MAX}			
Output Ripple (300Hz Vrms)	<0.4%			
Output Noise (40kHz-1MHz)	<0.1 Vrms			
Stability (CV, CC)	<± 0.05%			
Operating Temperature	5 - 40°C			
Temperature Coefficient (CV)	0.02% per °C			
Temperature Coefficient (CC)	0.03% per °C			
Temperature Coefficient (CV)	<0.02% of full scale value per°C			
Temperature Coefficient (CC)	<0.03% of full scale value per°C			
Dimensions (65V Module Only)	19" \times 9U \times 570mm (W \times H \times D), specific flight case dimensions are available on request			
Dimensions [46V Module Only]	19" \times 6U \times 495mm (W \times H \times D), specific flight case dimensions are available on request			
Weight (65V Module Only)	64kg, specific flight case weight is available on request			
Weight (46V Module Only)	44kg, specific flight case weight is available on request			

A more detailed technical summary is available on request

HIGHLIGHTED FEATURES

SENSE COMPENSATION

Sense plus terminals are built into modules for the connection of sense wire which compensates for voltage drops in the load lines. This has a number of advantages over traditional sense. It is permitted to interrupt the load line during operation (voltage on). The maximum voltage drop compensation is adjustable. The voltage difference between the module output and sensing point is monitored. If a set limit is exceeded, the module shuts off. This is particularly useful for applications with long cables often prone to unwanted voltage drops.

1mΩ 3200mΩ INTERNAL RESISTANCE RANGE

Each module is built with a user programmable internal resistance range as standard. This makes the power supplies ideal for simulating the ouput of energy storage devices such as battery packs, fuel cell stacks and super capacitors. The exact range varies by module and can be viewed in the selection table.

OPERATING RANGES AND FEATURES

65V LAB-GSS TECHNICAL DATA

GENERAL				
AC Line Voltage / Current Relationship	3 × 380VAC ± 10% / 54Arms [per 32kW module] 3 × 400VAC ± 10% / 51Arms [per 32kW module] 3 × 415VAC ± 10% / 49Arms [per 32kW module] 3 × 440VAC ± 10% / 47Arms [per 32kW module] 3 × 460VAC ± 10% / 45Arms [per 32kW module] 3 × 480VAC ± 10% / 43Arms [per 32kW module]			
Line Frequency	50Hz \pm 0.5Hz for UK (48 - 62Hz possible)			
Mains Connection Type	3L + PE (no neutral)			
Powerfactor [Q1 Active / Q4 Mode]	≥0.99			
Protective Conductor Current at 50Hz	<20mA			
Touch Current Unweighted	<20mA			
Touch Current Weighted	<2mA			
Isolation (Line to Case / Logic)	1670VDC 1s			
Isolation (Output to Case / Logic)	2060VDC 1s			
Isolation (Transformer)	4800VAC			
Isolation Output to Case	>10.8MΩ (35nF per DC bar)			
Isolation Output to Case (-bar and +bar)	+680VDC / -680VDC			
EMC Emissions and Immunity	EN61000-6-4 & EN61000-6-2			
Islanding for Generation to Public Grid	EN50438 & VDE0126			
LVD for Power Installations	EN50178			
Voltage Range	0 to 100% of Vmax			
Current Range	0 to ± 100% of Imax			
Power Range	0 to ± 100% of Pmax			
Internal Resistance Range	Adjustable $\Omega_{MAX} = [V_{NOM} / I_{NOM}]$			
Switchable Output Capacitance	6mF/ 17.2mF			
Standard Interfaces	Analogue and RS-232			
Available Interfaces on Request	HMI, USB, Ethernet and CANmp			
Voltage Sense Compensation	0 - V _{max}			
Efficiency	Up to 92%			
Load Regulation (CV, CC)	<± 0.1% of full scale value			
Line Regulation (CV, CC)	<± 0.1% of full scale value			
Temperature Coefficient (CV)	<0.02% of full scale value per°C			
Temperature Coefficient (CC)	<0.03% of full scale value per°C			
Response Time (Typical 10-90% Load Step Change)	1.1ms (with an ohmic load, at constant line and temperature)			
Over Voltage Protection	0 - 110% of V _{MAX}			
Over Current Protection	0 - 110% of I _{MAX}			
DC Ripple (≤300Hz)	<0.2%Vpp (<0.05%Vrms) of full scale value			
DC Noise (40kHz-1MHz)	<0.2Vpp (<0.05Vrms)			
Stability (CV, CC)	$<\pm$ 0.05% of full scale value			
Recommended Operating Temperature	5 - 40°C			
Weight (per Module)	97kg, flight case weight is available on request			
Connection to UK Grid	ER G59-3 tested			
Dimensions (per Module)	19" \times 9U \times 634mm (W \times H \times D), flight case dimensions are available on request			
Extended Technical Data is Available on Request				

Extended Technical Data is Available on Request





INTERFACES AND CONTROL

EXAMPLAND RS-232 INTERFACE

The RS-232 interface is configured as a Sub-D 9 pin connector (female) and is located on the front panel. The TopControl GUI is operated via RS-232. The software runs on Windows and allows the user to control, measure and configure the power system.

TECHNICAL DATA				
Isolation to Electronics and Earth Configuration	125 Vrms			
Baud Rate	38,400 baud			
Resolution (programming & readback)	0.025% FS (for V & I), 0.1% FS (for P & Ri)			

JATIE STANDARD ANALOGUE INTERFACE

The control port is configured as a Sub-D 25 female connector and is located on the rear panel. It allows output values to be set and read proportionally using a 0-10VDC analogue signal. Digital inputs and outputs enable various functions such as the interlock and output ON/OFF. A 10VDC reference is provided for analogue control. Digital functions are switched via a high/low signal. A 24VDC supply voltage is provided for these functions. The control port is labelled X105.

TECHNICAL DATA				
Isolation to Electronics and Earth	125 Vrms			
Unit Ready/Error	Relay Contact			
Ouput Voltage ON / Warnings	Relay Contact			
Actual Voltage Readback 0 - 100%	0 to 10V			
Actual Current Readback -100% to 100%	-10V to 10V			
Resolution (programming & readback) for V, I, P, Ri	0.2% FS			
Output Voltage Off/On	0/24VAC/DC			
2 Digital Application Inputs	0/24VAC/DC			
Interlock Circuit	0/24VDC			
Voltage Setting 0 to 100%	0 to 10V			
Current Setting -100% to 100%	-10V to 10V			
Power Setting 0% to 100%	+10V to 0V			
Internal Resistance Setting 0% to 100%	0V to 10V			



PIN	SIGNAL	I/O	DESCRIPTION	PIN	SIGNAL	I/O	DESCRIPTION
1	AGND	I	Analogue ground for pins 2–4, 14–16	16	VACT	0	Voltage feedback output 0–10 V
2	VREF	I	Voltage setpoint input 0–10 V	17	СОМ	I	[Connected to pin 7] Common ground to
3	IREF	1	Current setpoint input 0–10 V				pins 8–9, 18–20, 24
4	IACT	0	Current feedback output 0–10 V	18	APP_DIGITALIN_1	T	Digital input (low) 0-2 VDC/(high) 10–28 VDC
5	0VDC	0	0 VDC I/O ground for pin 251				Digital input
6	+10VDC	0	Analogue reference voltage	19	APP_DIGITALIN_2	I	(low) 0-2 VDC/(high) 10-28 VDC
7	СОМ	I	(Connected to pin 17) 0VDC DigIn; common ground for pins 8–9, 18–20, 24	20	APP_DIGITALIN_3; ANAOG_	I	Digital input [(low) 0-2 VDC/[high] 10–28 VDC
8	APP_DIGITALIN_4; CLEAR_ERROR	I	Digital input 0-2V /10-24V DC		SELECT		Analogue reference select
9	VOLTAGE_ON	I	Digital input 0-2/10-24V DC	21	WARN_a ²	0	Relay output 3 normally open
10	OK/ALARM b ²	0	Relay output 1 normally open	22	WARN_b ²	0	Relay output 3 normally closed
11	OK/ALARM_a ²	0	Relay output 1 common	23	WARN_c ²	0	Relay output 3 common
12	RUN_b ²	0	Relay output 2 normally open	24	INTERLOCK IN +	I	Input Interlock +
13	RUN_a ²	0	Relay output 2 common	21			
14	PREF	I	Power limit analogue input 0–10 V	25	+24VDC	0	Aux power output 24 VDC, max. 0.2 A
15	RREF	1	Ri-simulation analogue input 0–10 V				

¹ Pin 5 (0 VDC) is used as the reference earth for pin 25 (24 VDC) and is connected internally to the equipotential bonding via a 1 kΩ resistor to earth.

² Maximum switching current: 1 A; maximum switching voltage: 24 V.

Other inferfaces are available with rental modules on request, please contact ETPS to discuss a specific control method.

SOFTWARE/SOFT TOOLS

STANDARD TOP CONTROL GUI

All rental LAB-TC modules come with a simple and intuitive TopControl operating GUI. Live values of the power system are displayed graphically along with any warning and error messages. The software provides a variety of second level parameters, ideal for users who like to optimise their test processes. In standard user mode the operator can remotely program set values, enable voltage output as well as the ability to anlyse different variables including set and actual values via the integrated scope.

The scope function can simultaneously record up to 8 system variables. Recording can be started manually or by a defined trigger event from any variable of the system. All actual and set values (currents/voltages/power/internal resistance) can be recorded. Other recordable items include system temperatures, intermediate DC circuit, low voltage auxiliary power supplies, error related values and variables from the controller section.

A password protected section is available to the advanced user and service technician. In addition to the standard functions the authorised user is able to:

- + Program linear ramp functions at start up and set value steps during operation
- + Configure multi-unit operation
- + Program the PID controller parameters
- + Program the unit's limit values
- + Calibrate and adjust values as necessary
- + Update the firmware



FUNCTION GENERATOR

Complex DC waveforms can be implemented through an embedded function generator. The highly programmable nature of the function generator allows users to plot out exact waveforms. This is often advantageous when emulating a power device with a very

specific behaviour profile. For example, when quality testing fuel cell powered equipment, the specific behaviour of a discharging fuel cell can be programmed and replicated.

As well as custom shapes, standard square, sawtooth and sine waveforms can be plotted against time. Voltage/current and voltage/power relationships can also be programmed where necessary. Parametric programming is possible, where instead of the time axis, an input variable $[V_{IN}, I_{IN} \text{ or } P_{IN}]$ can be selected.





APPLICATION SPECIFIC GUIs

An application GUI can be used to program hardware to replicate real world behaviour of a power component. This allows specific sections of a circuit to be isolated and researched. Hard to replicate conditions, such as as cranking curve from a cold start, can also be programmed and repeated.

A selection of GUIs below are available with rental LAB-TC modules. Please enquire to ETPS if you require a specific program for your testing.

BATTERY EMULATION (/BATSIM)

BatSim provides a convenient method for the LAB-TC to emulate the output of different sized battery stacks. Nearly all relevant electrical characteristics are programmable, including the number of cells, energy capacity, cut off limits, chemistry type and nominal voltage.



CAPACITOR SIMULATION (/CAPSIM)

The output characteristics of a real capacitor stack can be emulated when CapSim is installed with LAB-TC modules. Number of cells in series/parallel, state of charge, cell cut off limits, dynamic capacitance and resistance are programmable.



ELECTRIC DRIVE CYCLING (/BATCONTROL)

Drive cycle tests can be implemented using BatControl. Previous data obtained from a test track can be imported and recreated, allowing the LAB-TC to simulate a real world driving test inside a lab environment. Battery charging profiles can also be implemented through the GUI.



SOLAR ARRAY SIMULATION (/SAS)

SASControl software has all EN 50530 tests pre-installed. The GUI allows users to edit irradiance, temperature and amplitude values. Previous tests have been conducted using over 400,000 invividual data points, with more possible.



NEW LAB-TC SYSTEMS

If you are looking to purchase a system, new LAB-TC modules can be found in our DC source range. A selection of options are available including integrated safety relays, an extended internal resistance range, reverse polarity protection, as well as a variety of interfaces. Ruggedised modifications are possible to guard against shock, vibration and humidity for harsh environments.

Where necessary, units can be treated to a laboratory rack or flight case integration. Common options include mains cables, passive indication of any residual DC voltage, isolation monitoring of DC cables and a panel mounted emergency stop. Switch panels with removable DC links can be fitted to simplify reconfiguration between series, parallel or independent use.

COMMON LAB-TC APPLICATIONS



に ジョ CRANKING CURVE TESTING

Electrical components within a vehicle's subsystem must be able to withstand a wide range of input voltage surges and drops during a start-up. The LAB-TC can accurately recreate these conditions within a lab environment. This increases reproducibility and accuracy of results when compared to using real batteries. Hard to replicate conditions such as voltage cranking during a cold start can be achieved. Voltage/current and voltage/power relationships can be programmed against time where necessary.



^{DC}∕_{AC} INVERTER/CONVERTER TESTING

The DC input of virtually any power conversion device can be replicated. The influence that variables, such as line voltage variation, have on performance can be isolated and tested. This allows optimum operating conditions to be characterised to improve efficiency and performance.



In electronic systems sudden voltage interruptions may cause unexpected behaviour. Supply line disturbances may have several causes, including an additional switch on of large capacitive loads parallel to the supply line or a short circuit caused by loads sharing the supply. The LAB-TC can generate many complex DC waveforms to test devices under realistic conditions to identify any potential issues.



(H_2) FUEL CELL EMULATION

The discharge behaviour of an FCEV's fuel cell is often irregular. By using the function generator, both conservative and agressive driver profiles can be replicated. This allows the LAB-TC to perform effective quality testing of fuel cell powered components under all likely operating conditions.



Every effort is made to ensure that the information provided within this technical summary is accurate. However, ETPS Ltd must reserve the right to make changes to the published specifications without prior notice. Where certain operating parameters are critical for your application we advise that they be confirmed at the time of order. ETPS Ltd specialises in modifying its proven platforms to suit your needs. Please contact our office if your requirement is non-standard. Please note that your actual unit may differ from those shown.





ETPS engineer electronic power supply and testing systems. Our problem solving skills provide the spark of innovation to some of the world's leading technology brands.





Tel: +44 (0) 1246 452909 Sales: 0800 612 95 75 sales@etps.co.uk www.etps.co.uk ETPS Ltd Unit 14, The Bridge Beresford Way, Chesterfield S41 9FG

POSITIVE PROBLEM SOLVING